

Type N F/F Coaxial RF Surge Protector, 800MHz - 2.25GHz, DC Block, Quarter Wave Stub, Low PIM



QWP-NFNFB

Features

- Broadband Performance from 800 to 2,250 MHz
- DC Block Topology
- Bi-directional, Repetitive Strike Protection
- Low PIM

Applications

- Distributed Antenna Systems (DAS)
- Emergency Response Systems
- Public Safety Systems
- Cellular

Description

RF surge protector (also known as lightning arrestor) QWP-NFNFB from PolyPhaser utilizing a quarter wave stub design to protect critical hardware while maintaining the RF performance. This RF surge protector component is manufactured in a coaxial in-line design with wide operating frequency range. PolyPhaser's RF surge protector products are available in stock with same day shipping.

Electrical Specifications

Surge Protector Type
DC Handling

Quarter Wave Stub
DC Block

Description	Minimum	Typical	Maximum	Units
Frequency Range	0.8		2.25	GHz
Impedance		50		Ohms
VSWR			1.2:1	
Insertion Loss			0.2	dB
Passive Intermodulation			-150	dBc
Input Power, CW			500	Watts

Mechanical Specifications

Size

Length	3.1 in [78.74 mm]
Width/Diameter	3.1 in [78.74 mm]
Height	1 in [25.4 mm]
Weight	0.6 lbs [272.16 g]
Housing Material and Plating	Brass, Tri-Metal

Configuration

Input Connector	N Female
Output Connector	N Female

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications:
[Type N F/F Coaxial RF Surge Protector, 800MHz - 2.25GHz, DC Block, Quarter Wave Stub, Low PIM QWP-NFNFB](#)

Type N F/F Coaxial RF Surge Protector, 800MHz -
2.25GHz, DC Block, Quarter Wave Stub, Low PIM



QWP-NFNFB

Environmental Specifications

Temperature

Operating Range

-40 to +85 deg C

Compliance Certifications

RoHS Compliant

Yes

Plotted and Other Data

Notes:

PolyPhaser protects and increases the reliability of global RF communications networks, including transportation, telecommunications, defense, security and industrial applications, with superior RF surge protection technologies including DC Block, DC Pass and Ultra Low PIM. Backed by responsive service and expert technical support PolyPhaser continually expands its product offering and services to serve engineers' urgent needs for RF components in mission critical communication networks.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [Type N F/F Coaxial RF Surge Protector, 800MHz - 2.25GHz, DC Block, Quarter Wave Stub, Low PIM QWP-NFNFB](https://www.polyphaser.com/type-n-surge-protector-2.25ghz-quarter-wave-stub-qwp-nfnfb-p.aspx)

URL: <https://www.polyphaser.com/type-n-surge-protector-2.25ghz-quarter-wave-stub-qwp-nfnfb-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. PolyPhaser reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. PolyPhaser does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and PolyPhaser does not assume any liability arising out of the use of any part or documentation.

