

NEX10 Male to NEX10 Female CBRN/Cellular RF Surge Protector, 555MHz - 4.5GHz, Low PIM



QWP-NXMNXF-ER

Features

- Extended Range Broadband Performance from 555 to 4500 MHz
- DC Block Topology
- Repetitive Strike Protection
- Low PIM

Applications

- CBRN Networks
- Cellular
- Distributed Antenna Systems (DAS)
- Emergency Response Systems
- Public Safety Systems

Description

RF surge protector (also known as lightning arrestor) QWP-NXMNXF-ER from PolyPhaser utilizing a quarter wave stub design to protect critical hardware while maintaining the RF performance. This RF surge protector component is manufactured in a coaxial in-line design with wide operating frequency range. PolyPhaser RF surge protector products are available in stock with same day shipping.

Electrical Specifications

Surge Protector Type		Quarter Wave Stub		
DC Handling		DC Block		
Description	Minimum	Typical	Maximum	Units
Frequency Range	0.555		4.5	GHz
Impedance		50		Ohms
VSWR			1.18:1	
Insertion Loss			0.1	dB
Passive Intermodulation			160	dBc
Input Power, CW			200	Watts
Surge Current			50	kA
IEC 61000-4-5 8/20μs				

Mechanical Specifications

Size

Length	3.09 in [78.49 mm]
Width/Diameter	0.98 in [24.89 mm]
Height	1.47 in [37.34 mm]
Weight	0.5 lbs [226.8 g]
Housing Material and Plating	Brass, Tri-Metal

Configuration


Input Connector	4.3-10 Male
Output Connector	4.3-10 Female

Environmental Specifications

Temperature

Operating Range	-40 to +85 deg C
Ingress Protection (IP) Rating	Pin to Shield

NEX10 Male to NEX10 Female CBRS/Cellular RF Surge Protector, 555MHz - 4.5GHz, Low PIM



QWP-NXMN XF-ER

Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Notes:

PolyPhaser protects and increases the reliability of global RF communications networks, including transportation, telecommunications, defense, security and industrial applications, with superior RF surge protection technologies including DC Block, DC Pass and Ultra Low PIM. Backed by responsive service and expert technical support PolyPhaser continually expands its product offering and services to serve engineers' urgent needs for RF components in mission critical communication networks.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [NEX10 Male to NEX10 Female CBRS/Cellular RF Surge Protector, 555MHz - 4.5GHz, Low PIM QWP-NXMN XF-ER](#)

URL: <https://www.polyphaser.com/surge-protector-4.5ghz-qwp-nxmxf-er-p.aspx>

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to implement improvements. PolyPhaser reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. PolyPhaser does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and PolyPhaser does not assume liability arising out of the use of any part or document.

QWP-NXMN XF-ER CAD Drawing

NEX10 Male to NEX10 Female CBRS/Cellular RF Surge Protector, 555MHz - 4.5GHz, Low PIM

